DIGITAL THERMOMETER

WT－1

Parameters

◆Temperature range: -50℃～+250℃ (-58℉～+482℉)
◆Distinguishing rate: 0.1℃
◆Accuracy: (-20℃～80℃)±1℃
◆Power voltage:DC 1.5V

Functions

◆Memory of the last measuring
◆Measuring and display low voltage
◆Saving power: auto-off after 15 minutes of no-operation
◆Sensor fault display
◆Switch between ℃ and ℉

Operation description

◆[ON/OFF]: Press the key to turn on/off the thermometer. When turn on it displays the last measuring temperature for 1.5 second then enters into measuring mode. Auto-off after 15 minutes of no-operation.
◆[℃/℉]: In the mode of temperature display press the key to switch between ℃ and ℉.
◆Measuring and display low voltage: when voltage lower than 1.3V LCD displays "LOW".
◆Display E00 when sensor open circuit or lower than measuring range; Display E11 when sensor short circuit or higher than measuring range.